

ScadaTec Technical Note

ScadaPhone – Command Line Switches

August 8, 2002

Purpose:

This note documents the command line switches available for the ScadaPhone program.

Applies To:

All versions from Version 4.2 up.

Note:

1. To have ScadaPhone load a specific project at startup:

`/PROJECT: <project-dir>`

If <project-dir> contains a space, bracket the path with double quotes.
examples:

`C: \ScadaTEC\ScadaPhone.exe /PROJECT: C: \Temp`

`C: \ScadaTEC\ScadaPhone.exe /PROJECT: "C: \My Documents\Temp"`

2. To force ScadaPhone to start up in a specific mode:

`/MODE: <RUN/DEVELOPMENT>`

examples:

`C: \ScadaTEC\ScadaPhone.exe /MODE: DEVELOPMENT`

`C: \ScadaTEC\ScadaPhone.exe /MODE: RUN`

If either `/PROJECT:` or `/MODE:` are not specified, the value from the INI file is used and ScadaPhone will start up in the same mode it was shut down in..

3. To bypass the log-in security system and eliminate the need to log in.:

`/NOSECURITY`

example:

`C: \ScadaTEC\ScadaPhone.exe /NOSECURITY`

4. To display Scadasis in the list of OLE servers:

`/OLE`

example:

`C: \ScadaTEC\ScadaPhone.exe /OLE`

5. To allow multiple copies of ScadaPhone to run simultaneously:

`/MULTINS`

example:

`C: \ScadaTEC\ScadaPhone.exe /MULTINS`